

Professional colour laser printer

Robust, high-quality, and designed for sustainable printing

Optimise your business workflow with the MFC-L8970CDW. Built to deliver high performance in a compact, eco-conscious design. With fast print and scan speeds, advanced connectivity, and robust security, this printer is designed to streamline workflows and boost productivity - without taking up a lot of space.

MFC-L8970CDW

Key features

- Print or copy up to 31 pages per minute (ppm)
- 2-Sided print or copy, up to 20 sides per minute (spm)
- Dual-band Wi-Fi (2.4GHz and 5GHz)
- Gigabit ethernet
- 250 sheet paper tray
- 50 sheet multi-purpose tray
- Auto paper low/empty detection
- 7,500 page black and 6,500 page colour in-box toners
- 10,000 page black and colour toners available
- Available under a managed print service (MPS) contract



FPOT
less than
9.9 seconds

17.6cm
(7.0") colour
touchscreen

2-Sided
scan up to
100ipm

NFC
secure
authentication

Sustainability

Reducing our environmental impact

- Increase printer life and reduce downtime with easy to replace parts
- 100% EPS-free packaging for easy recycling
- Designed and built to be remanufactured
- Made with up to 13% recycled plastic²⁷
- Up to 31% reduction in Typical Energy Consumption (TEC)²⁶
- Up to 12% reduction in CO₂ emissions²⁸
- Blue Angel certified for meeting high environmental standards



Workflow

Designed for business efficiency

- Monitor and control your Brother fleet with network-based management tools
- Boost efficiency with high-speed scanning for faster document processing

Productivity

Reliable performance, built to last

- Robust design, built for demanding businesses
- High yield toners keep you printing without interruptions
- Keep printing for longer with scalable paper capacity
- Streamlined design, up to 25% smaller than previous model



Secure by design

Device security

Your device protects your business by minimising attack surfaces through:

- Secure user access via LDAPS, Active Directory, and NFC authentication
- Controlled privileges using secure function lock and setting lock
- System integrity ensured by intrusion detection, Secure Boot, and digitally signed firmware

Network security

Your network is protected with flexible, industry-standard tools including:

- Intrusion protection through protocol control, interface restrictions, and IPv4 filtering
- Secure connections via IEEE 802.1X for enterprise wired and wireless networks
- Encrypted communication using TLS, SSH, IPSEC, HTTPS, and SNMPv3
- Centralised management with device master settings, BRAdmin Pro 4, and mass deployment tool
- Syslog reporting for seamless real-time SIEM integration

Document security

Your documents are protected through:

- Encrypted transfer via IPPS/HTTPS for printing and TLS, HTTPS, SFTP for scanning
- Non-persistent memory, ensuring data is wiped after each job or reboot
- Secure print release, so documents only print when you're ready to collect them
- Third-party integration via Brother Solutions Interface (BSI), to streamline workflows

Brother MPS

Make printing simple with Brother MPS

Managed Print Services (MPS) ensure you maximise the performance and value of your print devices. Whatever your printing needs, we'll be "At your side" to find the solution that simplifies printer admin, saves time, keeps costs down, and helps you stay productive.

Benefits include:

- No long-term commitments
- Ink and toner delivery before you run out
- Quick breakdown support
- Easy supplies recycling



Supplies

Toners



- TN625**
3,000 BK, 1,800 C,M,Y
- TN625XL**
5,500 BK, 4,500 C,M,Y
- TN625XXL (in-box)**
7,500 BK, 6,500 C,M,Y
- TN627**
10,000 BK, 10,000 C,M,Y

Accessories


Trays and cabinet

- LT350CL**
250 sheet lower tray
- LT360CL**
520 sheet lower tray
- ZUNTBC4FARBLASER**
Floor standing cabinet

Replaceable parts



Drum unit
DR625CL



Belt unit
BU635CL



Waste toner box
WT229CL



Fuser unit
FD5000

Paper feed kit
for MP tray
PFM5000



General

Technology

Electrophotographic (laser)

Laser classification

Class 1 laser product

Memory

1GB internal

Processor

1200MHz

Control panel

17.6cm (7") colour
touchscreen LCD

Local interface¹⁸

Hi-speed USB 2.0,
USB 2.0 host (front | rear)

Wired network interface

GigE (10Base-T/100Base-
TX/1000Base-T)

Fax interface

Telephone line port
External telephone answering
device port (TAD)

Configurable shortcuts

Add, delete and change up to
64 personalised shortcuts for
quick and secure access to
device functions

Wireless network interface

2.4GHz: IEEE 802.11b/g/n
5GHz¹⁷: IEEE 802.11a/n
(infrastructure mode),
vertical pairing

Wi-Fi Direct[®]

Print wirelessly without having
to use a wireless access point
(both automatic and manual
methods supported)

Dedicated UI

Group registered shortcuts and
link it to each user, shortcuts can
be displayed as home tab just
after login

Print^{9,24}

Print speed (A4)

Up to 31ppm

Print speed 2-Sided (A4)

Up to 20spm
(10 sheets per minute)

Resolution

2,400dpi (2,400 x 600dpi),
600 x 600dpi
(horizontal x vertical,
dots per inch)

First print out time (FPOT)

Less than 9.9 seconds from
ready mode and standard tray

Warm up time

Less than 15.1 seconds from
sleep mode

Driverless printing compatibility

Windows modern print platform ready

Supports seamless, driverless
printing via IPP for instant setup
on Windows 10 (21H2+) and
Windows 11 devices

Mopria

Print common file types
from supported Android
mobile devices and Windows
computers

Apple AirPrint

Print common file types from any
AirPrint enabled application

ChromeOS™

Supports work with
Chromebook printing

Our printers support driverless printing across Windows, macOS, iOS, and Android devices for instant, secure, and hassle-free setup

Printer functions

Direct print

Print directly from the front or rear USB host port using a USB flash memory drive. Supported formats include: PDF 2.0, JPEG, TIFF (scanned using Brother model)

Print complete notice

A notification can be set to go to your computer when printing

Manual 2-Sided print^{4,25}

Manual 2-Sided printing recommended for media not supported by automatic 2-Sided print

Carbon copy⁴

Prints additional copies of the same document to paper taken from additional paper trays

Header footer print^{3,25}

Add the date, time, login user name, or custom text to the top or bottom of each printed page

Skip tray¹⁹

Configures your paper tray selection to avoid specific trays/media for regular printing

N-up printing³

Reduce up to 2, 4, 9, 16 or 25 A4 pages into just one A4 page, Mac (Airprint) up to 2, 4, 6, 9, or 16

Poster printing^{4,25}

Enlarge 1 A4 page into a poster using 4, 9, 16 or 25 A4 pages

Watermark printing^{3,25}

Watermark your documents with predefined or user-defined text

Secure print³

Protect print jobs with a release code required at the device in order for them to be printed

Reverse print^{4,25}

Rotate the content of a printed document by 180°

Storage print

Easily retrieve and print your documents or reprint stored documents all of which are AES 256 encrypted and held within an attached USB flash memory drive storage (not included) via the rear port

Paper handling

Paper input²

Standard (tray 1)

250 sheets

Multi-purpose tray

50 sheets, 10 envelopes

ADF

80 sheets

Paper output²

150 sheets face down

1 sheet face up (straight path)

Media sizes

Standard (tray 1)

Letter, legal, executive, A4, A5, A5 (long edge), A6, Mexico legal, India legal, folio, 16K (195 x 270mm)

Multi-purpose tray

Width: 76.2mm - 216mm

Length: 116mm - 355.6mm

Envelopes: C5, Com-10,

DL, Monarch

Optional trays

Letter, legal, executive, A4, A5, Mexico legal, India legal, folio, 16K (195 x 270mm)

ADF

Width: 105 - 215.9mm

Length: 148 - 355.6mm

Media weights

Standard (tray 1)

60 - 105gsm

Multi-purpose tray

60 - 163gsm

Optional trays

60 - 105gsm

ADF

60 - 105gsm

Media types

Standard (tray 1)

Thin paper, plain paper, thick paper, recycled paper

Multi-purpose tray

Thin paper, plain paper, thick paper, recycled paper, bond paper, label, envelope, env. thin, env. thick, glossy paper²⁰

Optional trays

Thin paper, plain paper, recycled paper

Auto 2-sided print

Thin paper, plain paper, thick paper, thicker paper, recycled paper, glossy paper

ADF

Thin paper, plain paper, recycled paper

Paper input sensors

On-screen and optional email alert notifications when input trays are empty or running low

Copy¹⁰

Copy speed (A4)

Up to 31 copies per minute (cpm)

Copy speed 2-Sided (A4)

Up to 20spm
(10 sheets per minute)

First copy out time (FCOT)

12.5 seconds from ready mode and standard tray

Resolution

Print up to 1,200 x 600dpi (horizontal x vertical, dots per inch)

Copy functions

Multi-copying

Ensures that your copies are organised in the correct order, making it easier to manage large documents. Makes up to 999 copies of each page

Copy interrupt

You can configure the machine to interrupt a print job in progress at any time to print another copy function job

Enlargement/reduction ratio

Reduce or increase document sizes from 25% to 400% in 1% increments

Automatic 2-sided copying

Scans and copies documents using the ADF

N in 1 copying

Allows the user to compress 2 or 4 pages on to a single A4 sheet

Scan

Scan speed standard (A4)

(2 Sided)¹¹ up to 100 images per minute(ipm) colour and mono

Optical scan resolution

ADF up to 600 x 600dpi, flatbed up to 1,200 x 1,200dpi (horizontal x vertical, dots per inch)

Interpolated scan resolution²²

Up to 19,200 x 19,200dpi, (horizontal x vertical, dots per inch)

Scanner type

Dual contact image sensor (CIS)

Colour depth

48 bit colour processing (input)
24 bit colour processing (output)

Grey scale

256 levels (8 bit)

Scanner functions

Windows⁵

TWAIN and WIA

Macintosh²³

AirPrint scanning
macOS 10.14.x or greater

Linux⁵

SANE (32 and 64 bit editions)

Machine file formats

Including PDF (PDF/A, secure PDF, signed PDF, high compression PDF, multi-page PDF), JPEG, TIFF

Standard machine functions⁷

Scan to USB, email, OCR, image and file

Network scanning

Scan to network folder (SMB)⁴, SFTP, FTPS, email server, HTTPS, SharePoint (on premise)

Machine scanning features

Auto Deskew from ADF, background colour drop, auto crop, blank page removal

Scan profile

Create up to 25 preset network profiles for an easy way to store multiple scan settings

Direct scan

Scan directly to a USB flash memory storage

ChromeOS™

Supports integrated Chrome OS scanning functionality

Scan preview

The contents of scan to FTP, network, email server, HTTP, Sharepoint (on premise) can be checked before sending to destination

Scan margin

Setting the scan margin to 0mm removes the default 3mm margin, allowing the scanned image to capture the entire document without any border

Document separation

Create scanned files based on blank sheet separation or a specific number of single sided images or sheets of paper, even if more documents are set on the ADF

Document reminder

Alerts the user when a scanned or copied document may have been left behind on the flatbed scanner glass

Fax

Fax modem

33,600bps (Super G3)

Transmission speed

Approx. 2.5 sec (ITU-T TestChart document No.1, standard resolution, JBIG) quick-scan approx. 1.82 sec/page

Fax send resolution

Standard resolution 203 x 98dpi up to a maximum of 203 x 392dpi (horizontal x vertical, dots per inch)

Automatic 2-Sided faxing

Scans and faxes documents using the ADF

Grey scale

256 shades (8 bit) of grey are available for faxing

Memory transmission | out of paper reception

Up to 500 pages (ITU-T Test Chart, standard resolution, JBIG)

Compression methods

Ranging from basic to advanced with MH, MR, MMR, JBIG

Fax functions

PC-Fax send⁷ and receive^{4,7}

Send and receive black and white faxes directly from your PC

Internet fax (I-Fax)

Fax documents over the internet as an email TIFF attachment

Fax to server

Scan a document and send it over the network to a separate fax server

Automatic redial

Automatic redialling if the recipient fax is busy

Telephone index

An electronic, alphabetical listing of stored speed dials and group numbers

Chain dialing

Allows the user to store parts for long dialing sequences in different speed dial locations

Dial restriction

Restrict number dialing to prevent unauthorised or accidental outbound calls

Distinctive ring detection

An external service for UK and Denmark that allows two or more telephone numbers shared on a single fixed line and use different ring tones

Error correction mode

ECM detects line errors during fax transmission and resend the page(s) of the document that had an error (recipient machines must share this feature for it to work)

Batch transmission

Stores documents for the same location in the machines memory for transmission in a single call

Auto reduction

When receiving a single page document longer than A4 (297mm) the fax machine will automatically reduce the message to fit onto a single A4 sheet

Broadcasting

Send the same fax message up to 350 locations (manual 50 locations)

Fax forwarding

Sends a fax received in memory to another pre-programmed fax number

Remote retrieval

Allows users to remotely access their machine and retrieve stored fax messages

Fax stamp

Add the date and time to all received faxes

Cover page

Create custom cover pages for outgoing faxes

Station ID

An ID and fax number will be printed as the header of every fax sent

PBX

Enables seamless fax operation in office environments by supporting PBX phone systems

Connectivity

Mobile Connect

Use a Brother app to print from and scan to a mobile device running iOS or Android operating system

Brother Print Service Plugin⁵

Print from Android devices without a dedicated app

Microsoft Universal Print

Organisations can manage their brother print infrastructure through cloud services from Microsoft

Alexa print¹⁷

Print using Echo device and printer connected to the same network

Brother apps¹²

Cloud secure print, scan to; mobile, searchable PDF, Microsoft PowerPoint, Word, Excel, easy scan to email, and fax forward to cloud/email

Web Connect^{12,16}

Without a PC you can download to print and upload from scan and fax for Box, Microsoft SharePoint Online, Dropbox, Evernote, OneDrive, Google Drive™, OneNote

Email print^{12,16}

Enables driverless printing via email

Fleet management tools⁵

BRAdmin⁴

LAN/WAN management software

Clone device settings

Copy settings and configurations from one machine to another via a USB flash drive

Auto pull configuration

The device periodically checks an encrypted settings file on a network location. If the device has been changed the file is used to change back to the desired state configuration

Embedded web server

Using the IP address or node name of your device access via USB or network via a web browser to the web based print management software embedded onto the device using a randomly encrypted password

Mass deployment tool

Provides a configuration interface to help manage and deploy device settings.

Software⁵

Brother iPrint&Scan

Print from, scan to, send faxes, preview received faxes, preview copies and check the machine status from Windows or macOS PC using Brother software

Print support app⁴

As an alternative to Windows Modern Print this method enhances compatibility and ease of use by enabling printing without traditional printer drivers, making it a versatile and efficient solution for modern printing needs accessible through the Microsoft Store

Visit: support.brother.com for the full list of supported OS and to download the latest software
All trademarks, brand and product names are property of their respective companies

Legacy printer drivers²⁴

PCL driver⁴

Generic PCL XL driver

Universal printer driver⁴

BR-script3 driver that enables printing to any network or locally connected Brother laser printer that supports PostScript

Print languages

PCL6, BR-Script3

Embedded fonts (PCL)

73 scalable fonts, 12 bitmap fonts

Embedded fonts (BR-script)

66 scalable fonts

Embedded barcodes (PCL)

16 bar codes fonts - Code39, Interleaved 2 of 5, FIM (US-PostNet), Post Net (US-PostNet), EAN-8, EAN-13, UPC-A, UPC-E, Codabar, ISBN (EAN), ISBN (UPC-E), Code128 (set A,B, C), EAN128 (set A,B,C), Code93, GS1Databar, MSI

Linux

Printer driver (Linux, CUPS, LPD/LPRng)

Network security

Wired network security

APOP, SMTP-AUTH, SSL/TLS (IPP, HTTP, SMTP, POP3, IMAP4, FTP, LDAP), SNMP v3, 802.1x (EAP-MD5, EAP-FAST, PEAP, EAP-TLS, EAP-TTLS), OAuth(SMTP, POP3, IMAP4), Kerberos, IPsec

Wireless network security

WEP 64/128 bit, WPA-PSK (TKIP/AES), WPA2-PSK (TKIP/AES), WPA3-SAE (AES), APOP, SMTP-AUTH, SSL/TLS (IPP, HTTP, SMTP, POP3, IMAP4, FTP, LDAP), SNMP v3, 802.1x (EAP-FAST, PEAP, EAP-TLS, EAP-TTLS), OAuth (SMTP, POP3, IMAP4), Kerberos, IPsec Wi-Fi Protected Setup® (WPS)¹³

IPv4

ARP, RARP, BOOTP, DHCP, APIPA (Auto IP), WINS/NetBIOS name resolution, DNS Resolver, mDNS, LLNMR responder, LPR/LPD, Custom Raw Port/Port 9100, POP3, SMTP Client, IPP/PPS, FTP Client and Server, CIFS Client, TELNET Server, SNMPv1/v2c/v3, HTTP/HTTPS server, TFTP client and server, ICMP, web services (print/scan), SNTP Client, LDAP, LDAPS, IMAP4, syslog

Display IP address

The dynamic IP assigned to your device can be displayed on the home screen

IPv6

NDP, RA, DNS resolver, mDNS, LLNMR responder, LPR/LPD, Custom Raw Port/Port 9100, IPP/PPS, POP3, SMTP Client, FTP Client and Server, CIFS Client, TELNET Server, SNMPv1/v2c/v3, HTTP/HTTPS server, TFTP client and server, ICMPv6, web services (print/scan), SNTP Client, LDAP, LDAPS, IMAP4, syslog

IP filter

Restrict which network users can or cannot access the device over the network

Security features

Email notifications

Automatically have the device send email alerts when it requires attention, such as when the toner is low or needs replacing

Email reports

Receive usage reports on a regular basis via email

Secure boot

All Brother Print devices are secure by design. Devices automatically recognise security attacks and take preventative measures, including rebooting where necessary, in order to ensure the device remains secure

Digitally-signed firmware

The firmware for Brother print and scan devices is digitally signed and secure

Active Directory/LDAP authentication

Utilise existing infrastructure to restrict access to Brother devices using AD/LDAP. Staff can easily use their existing network login credentials to authenticate

Port-based network access control

(IEEE 802.1x) Brother devices are in full compliance with this standard, to allow connection to an 802.1x EAP (extensible authentication protocol) protected network

Restrict network protocols

The network access control feature allows an administrator to restrict communication protocols (e.g. FTP, Telnet) as required

Setting lock

Configure secure access to the devices control panel by locking individual features

Secure function lock 3.0

Use a four digit pin or a password to identify and authenticate an individual or groups of users over a network. Allows access control with username for up to 200 users

Cloud secure print¹²

Enables password protected driverless print job release

Store print log

Allows audit of a print log file saved to CIFS server. Record ID, type, name, user, date, time, page count for every print job

Firmware updates

In addition to allowing automatic updates to the latest version the printer can be set to not receive older firmware versions to avoid downgrade by an unauthorised user

Syslog

Allows IT admin to access a single application (SIEM tool) to get device status updates for audit purposes over syslog

Secure key management

Use the default standard self-signed, create a custom self-signed certificate, certificate signing request (CSR), or import certificate and private key for protected network communication (Type: RSA max size: 4,096 bit)

Near-field communications (NFC)

NFC card reader

Supports secure user authentication via NFC card reader for access control, and enables personalised workflows through NFC shortcut configuration. Third-party card reader support requires additional purchase and can be connected to the front or rear USB host and registered via the embedded web server

Integrated support for NFC

include: (ISO14443 Type A) MIFARE Standard / Plus / Ultralight / Ultralight C / DESfire / my-d move (ISO15693 Type B) Tag-it

External NFC card reader support

RFIDeas pcProx Enroll - RDR-6081AKU; RDR-6281AKU; RDR-6381AKU; RDR-6E81AKU; RDR-6H81AKU
RFIDeas AIR ID Enroll - RDR-7081AKU; RDR-7581AKU; RDR-7F81AKU
Elatec - TWN3 MIFARE; TWN3 MIFARE NFC; TWN3 Multi ISO; TWN4 MIFARE NFC

Address book

Speed dials

300 locations for email addresses and fax numbers

Group dial

A combination of up to 20 groups can be stored

LDAP

The ability to connect to an external LDAP enabled address book, like Microsoft Exchange

Developers

Brother Solutions Interface (BSI)

Create powerful cloud and on premise solutions directly integrating the advanced print, scan and security capabilities of Brother devices. For more information visit: www.brother.eu/developers

Supplies¹, upgrades and accessories

Standard toner

TN625
3,000 pages (BK)
1,800 pages (C,M,Y)

High yield toner

TN625XL
5,500 pages (BK)
4,500 pages (C,M,Y)

Super high yield toner (in-box)

TN625XXL
7,500 pages (BK)
6,500 pages (C,M,Y)

Ultra-high yield toner

TN627
10,000 pages (BK)
10,000 pages (C,M,Y)

Drum unit

DR625CL approx 50,000 pages at 3 pages per job

Belt unit

BU635CL approx. 100,000 pages at 3 pages per job

Waste toner box

WT229CL approx 50,000 pages at 5 pages per job

Fuser unit

FD5000 approx 100,000 pages at 5 pages per job

Paper feed kit for MP tray

PFM5000 approx 50,000 pages at 5 pages per job

Carton contents

Machine, in-box toners, drum, belt, waste toner box, fuser, PF kit, power supply cord, quick set-up guide, warranty card, (PC interface cable NOT included)

Optional paper trays²

250 sheet tray (LT350CL)
520 sheet tray (LT360CL)
Maximum combinations of up to 2 x LT350CL or 2 x LT360CL, 1 x LT350CL and 1 x LT360CL

Optional cabinet

ZUNTBC4FARBLASER Brother professional colour laser floor standing printer cabinet

Dimensions and weights (WxDxH)

Printer without carton
454 x 505 x 460mm - 26.7kg
inc. TN/DR/WT/BU/FD/PF

Printer with carton
650 x 610 x 643mm - 34.7kg

Optional paper trays
250 sheet tray:
404 x 446 x 100mm - 3.25kg
520 sheet tray:
404 x 446 x 131mm - 4.33kg

Optional cabinet without carton
410 x 484 x 400mm - 10kg

Duty cycle

Recommended monthly
Up to 7,500 pages monthly
print volume

Maximum monthly⁶
Up to 80,000 pages monthly
print volume
Up to 10,000 pages monthly
scan volume

Environment

Power requirement
AC 220-240V, 50/60Hz

Power consumption¹⁴
Printing: 540W
(330W in quiet mode)
Copying: 540W
(330W in quiet mode)
Ready: 60W
Sleep: 8.4W
Networked standby: 7.8W
Deep sleep: 0.53W
Power off: 0.04W

Sound pressure¹⁵
Printing: 49dbA
Quiet print mode: 44dbA
Default ready: 31dbA

Sound power¹⁵
Printing: 6.47BA
Quiet print mode: 5.88BA
Default ready: 4.43BA
Deep sleep: 3.38BA

TEC value
0.43 kWh/week

Eco mode
With seamless functionality
the eco control system of the
printer is designed to ensure
lower noise levels, consume
less energy when not in use and
optimise toner usage which all
help to reduce the total cost of
ownership

Operating environment
Humidity: 20 - 80%
Temp: 10° - 32.5° centigrade
50° - 90.5° fahrenheit

Storage environment
Humidity: 35 - 85%
Temp 0°: 40° centigrade
32° - 104° fahrenheit

Computer platforms

Windows
Windows 11
(Home|Pro|Education|Enterprise)
Windows 10
(Home|Pro|Education|Enterprise)
(32 or 64 bit editions)
Windows server
2025, 2022, 2019, 2016

Linux
Supported package
management system:²³
dpkg, rpm

Macintosh²¹
macOS 13 or greater

ChromeOS™
Compatible with Chromebooks,
including "Works with
Chromebook" certified printing
support and integrated Chrome
OS scanning functionality

Visit: support.brother.com for the full list of supported OS and to download the latest software

Disk space requirements

80MB Windows drivers
only, 2GB Windows 11, 10,
applications inc drivers

500MB - macOS applications

20MB - Linux drivers only

Visit: support.brother.com for the full list of supported OS and to download the latest software.
All trademarks, brand and product names are property of their respective companies

Certification

Blue Angel

Nordic Swan

GS Mark

AirPrint

Wi-Fi certified

Wi-Fi Direct, Wi-Fi Protected Setup, WPA3™ - Enterprise, Personal

Mopria certified

Ensures universal compatibility for driverless printing across Windows, Android, and compatible mobile operating systems

1. Approx declared toner yield value in accordance with ISO/IEC 19798. 2. Calculated with 80gsm sheets of paper. 3. Windows & macOS. 4. Windows only. 5. Free download from the Brother solutions centre <http://solutions.brother.com> 6. Number of printed pages per month can be used to compare designed durability between Brother products. For maximum printer life, it is best to choose a printer with a duty cycle that exceeds your print requirements. 7. Requires Brother software. 8. Based on ISO/IEC 24734. 9. Based on ISO/IEC 17629. 10. Based on ISO/IEC 24735. 11. Based on ISO/IEC 17991. 12. Requires an internet connection. 13. Wi-Fi Direct supports WPA2-PSK (AES) only. 14. Measured according to IEC 62301 Edition 2.0. All values are approximate; power consumption varies depending on the usage environment or part wear. 15. Based on ISO 7779. 16. Requires additional activation. 17. May not be available in your region. 18. Third party USB hubs not supported. 19. Requires installation of optional trays. 20. Set only a single sheet. 21. On macOS AirPrint only. 22. For WIA, 1,200 x 1,200 resolution. Brother scanner utility enables to enhance up to 19,200 x 19,200 dpi. 23. Red Hat Enterprise Linux 8.6 64bit, Red Hat Enterprise Linux 9.1 64bit, Fedora 39 64bit, Mageia 9 32bit, Mageia 9 64bit, openSUSE 15.5 64bit, SUSE Enterprise15-SP4 64bit, Debian 12.2.0 32bit, Debian 12.2.0 64bit, Ubuntu MATE 18.04 32bit, Ubuntu 22.04 64bit, Ubuntu 23.10 64bit, Linux Mint 21.2 64bit, Ubuntu 24.04 64bit. 24. Microsoft is transitioning towards driverless printing as the preferred standard. Legacy driver installations remain supported for customers with existing deployment requirements. 25. Advanced settings via legacy driver or the print support app only. 26. Compared to Brother's previous equivalent model. 27. Figure based on Brother's internal analysis at the time of publication. Figures may fluctuate depending on manufacturing methods and the availability of materials. 28. These results are based on Brother's internal calculations, compared to previous equivalent model. The CO₂ emissions scope covers C1 (purchased goods and services), C11 (use of sold products), and C12 (end-of-life treatment of sold products). Exact values may vary depending on country or region, manufacturing methods and the availability of materials.



brother
at your side



Working with you for a better environment

At Brother, our green initiative is simple. We strive to take responsibility, act respectfully and try to make a positive difference to help build a society where sustainable development can be achieved. We call this approach Brother Earth.

www.brotherearth.com

All specifications correct at the time of printing and are subject to change. Brother is a registered trademark of Brother Industries Ltd. Brand product names are registered trademarks or trademarks of their respective companies.